

# N600 Wireless Dual Band USB Adapter

## WF2151



### Features:

- >Wireless speed up to 2.4GHz 300Mbps and 5GHz 300Mbps
- >Easy wireless security encryption with single WPS button
- >Bundle with a stylish USB cradle for flexible deployment
- >2\*5dBi high gain detachable antennas provide better wireless signal coverage and reception
- >Auto Hassle free installation

### Brief:

The netis WF2151 N600 Wireless Dual Band USB Adapter is dedicated to the Dual Band wireless solutions. It provides you the access to crystal clear 5GHz connections or legacy 2.4GHz connections at 300Mbps. With the wireless connection transmitting over 5GHz band, you needn't worry about the interferences from the mass of existing 2.4GHz wireless devices and household appliances that may disturb with their wireless signal, ensuring a high-quality connection ideal for online gaming, video streaming, and VoIP phone calling. 5dBi detachable antenna allows for better alignment and stronger antenna upgrade.

[www.netis-systems.com](http://www.netis-systems.com)

## N600 Wireless Dual Band USB Adapter

# WF2151

### Specification:

Wireless			
Standards	IEEE 802.11a,IEEE 802.11b, IEEE 802.11g, IEEE 802.11n		
Signal Rate	Up to 300Mbps		
Frequency Range	2.4-2.4835GHz	5.15GHz-5.825GHz	
Mode	Infrastructure		
Wireless Security	Support 64/128-bit WEP, WPA-PSK/WPA2-PSK		
Hardware			
Port	USB 2.0		
Button	WPS		
Antenna	2*5dBi, Detachable Antennas		
Dimensions (L x W x H )	92.5 x 27 x 15 mm		
Weight	66.7g		
Others			
Certification	FCC, CE, KC		
Compatibility	Windows XP (32/64bits), Windows Vista (32/64bits), Windows 7 (32/64bits), Windows 8 (32/64bits), Windows 8.1 (32/64bits), MAC 10.4/10.5/10.6/10.7/10.8/10.9 Linux as Ubuntu 12.04/11.04		
Environment	Operating Temperature: 0°C~40°C Operating Humidity: 10%~90% non-condensing		Storage Temperature: -40°C~70°C Storage Humidity: 5%~90% non-condensing
Package	1 *WF2151	1 * Quick Installation Guide	1 * Driver CD

### Topological Graph:

